

Orthogonal–Phase–Velocity Propagation of Electromagnetic Plane Waves

Tom G. Mackay¹

School of Mathematics, University of Edinburgh, Edinburgh EH9 3JZ, UK

Akhlesh Lakhtakia

CATMAS — Computational & Theoretical Materials Sciences Group

Department of Engineering Science and Mechanics

Pennsylvania State University, University Park, PA 16802–6812, USA

Abstract

In an isotropic, homogeneous, nondissipative, dielectric–magnetic medium that is simply moving with respect to an inertial reference frame, planewave solutions of the Maxwell curl postulates can be such that the phase velocity and the time–averaged Poynting vector are mutually orthogonal. Orthogonal–phase–velocity propagation thus adds to the conventional positive–phase–velocity propagation and the recently discovered negative–phase–velocity propagation that is associated with the phenomenon of negative refraction.

Keywords: Minkowski constitutive relations, Poynting vector, Special theory of relativity

1 Introduction

Until quite recently, it was commonly held that the time–averaged Poynting vector and the phase velocity of a plane wave in any homogeneous and isotropic medium are coparallel [1, 2]; furthermore, the angle between the two vectors was commonly thought to be acute in homogeneous anisotropic mediums [3]. The successful fabrication of what are called negative–phase–velocity (NPV) materials² — in contrast to their conventional counterparts, the positive–phase–velocity (PPV) materials — led to a radical re–think: the angle between the two vectors can be obtuse and even 180°. Much has been written on NPV materials during the past five years, and we refer the interested reader to three pedagogical reviews [4, 5, 6] and two Focus Issues of electronic journals [7, 8].

Could there be materials that are neither of the PPV nor of the NPV types? We have already provided an affirmative answer to this question: there can be isotropic dielectric–magnetic materials wherein the phase velocity is infinite at some frequency [9]. In addition

¹Corresponding Author. Fax: + 44 131 650 6553; e–mail: T.Mackay@ed.ac.uk.

²Some researchers prefer the infelicitous term *left–handed materials*.

to the infinite-phase-velocity materials, we provide here a second affirmative answer: materials in which the phase velocity is orthogonal to the time-averaged Poynting vector. Such materials may be called orthogonal-phase-velocity (OPV) materials.

The OPV materials emerge here as a gift of the special theory of relativity [10, 11, 12]. Relative to a co-moving observer, these materials are supposed to be homogeneous, isotropic, and with dielectric and/or magnetic properties. Relative to an inertial observer that is not co-moving, planewave propagation may occur such that the OPV condition is satisfied. The OPV condition, however, will never be satisfied for the co-moving observer.

The plan of this paper is as follows: Section 2 is devoted to the Minkowski constitutive relations, planewave propagation, and the OPV condition. Section 3 contains numerical results for an OPV material that is non-dissipative. Conclusions are presented in Section 4. In the notation adopted, $\text{Re}\{Q\}$ and $\text{Im}\{Q\}$ represent the real and imaginary parts, respectively, of a complex-valued Q . The complex conjugate is written as Q^* . Vectors are identified by bold typeface and 3×3 dyadics are double underlined; $\hat{\mathbf{v}}$ is a unit vector co-directional with $\mathbf{v}$; the unit dyadic is $\underline{\underline{I}}$; and $\mathbf{r}$ denotes the spatial coordinate vector. The permittivity and permeability of free space (i.e., vacuum) are ϵ_0 and μ_0 , respectively; $c_0 = (\epsilon_0\mu_0)^{-1/2}$ is the speed of light in free space; ω is the angular frequency; and $k_0 = \omega/c_0$.

2 Analysis

2.1 Minkowski constitutive relations

As in a predecessor paper [13], two inertial reference frames, Σ and Σ' , provide the setting for our analysis. The inertial reference frame Σ' moves at constant velocity $\mathbf{v} = v\hat{\mathbf{v}}$ relative to the inertial reference frame Σ . The electromagnetic field phasors in frames Σ and Σ' are represented as $\{\mathbf{D}, \mathbf{E}, \mathbf{H}, \mathbf{B}\}$ and $\{\mathbf{D}', \mathbf{E}', \mathbf{H}', \mathbf{B}'\}$, respectively. The two sets of phasors are related via the Lorentz transformation as [10]

$$\mathbf{E}' = (\mathbf{E} \cdot \hat{\mathbf{v}}) \hat{\mathbf{v}} + \frac{1}{\sqrt{1 - \beta^2}} [(\underline{\underline{I}} - \hat{\mathbf{v}}\hat{\mathbf{v}}) \cdot \mathbf{E} + \mathbf{v} \times \mathbf{B}], \quad (1)$$

$$\mathbf{B}' = (\mathbf{B} \cdot \hat{\mathbf{v}}) \hat{\mathbf{v}} + \frac{1}{\sqrt{1 - \beta^2}} [(\underline{\underline{I}} - \hat{\mathbf{v}}\hat{\mathbf{v}}) \cdot \mathbf{B} - \frac{\mathbf{v} \times \mathbf{E}}{c_0^2}], \quad (2)$$

$$\mathbf{H}' = (\mathbf{H} \cdot \hat{\mathbf{v}}) \hat{\mathbf{v}} + \frac{1}{\sqrt{1 - \beta^2}} [(\underline{\underline{I}} - \hat{\mathbf{v}}\hat{\mathbf{v}}) \cdot \mathbf{H} - \mathbf{v} \times \mathbf{D}], \quad (3)$$

$$\mathbf{D}' = (\mathbf{D} \cdot \hat{\mathbf{v}}) \hat{\mathbf{v}} + \frac{1}{\sqrt{1 - \beta^2}} [(\underline{\underline{I}} - \hat{\mathbf{v}}\hat{\mathbf{v}}) \cdot \mathbf{D} + \frac{\mathbf{v} \times \mathbf{H}}{c_0^2}], \quad (4)$$

where $\beta = v/c_0$.

We consider a homogeneous medium which is characterized by the frequency-domain dielectric-magnetic constitutive relations

$$\left. \begin{aligned} \mathbf{D}' &= \epsilon_0 \epsilon_r \mathbf{E}' \\ \mathbf{B}' &= \mu_0 \mu_r \mathbf{B}' \end{aligned} \right\}, \quad (5)$$

in the co-moving reference frame Σ' , with ϵ_r as the relative permittivity and μ_r as the relative permeability. By virtue of (1)–(4), the constitutive relations (5) transform to the Minkowski constitutive relations

$$\left. \begin{aligned} \mathbf{D} &= \epsilon_0 \epsilon_r \underline{\underline{\alpha}} \cdot \mathbf{E} + \frac{m \hat{\mathbf{v}} \times \mathbf{H}}{c_0} \\ \mathbf{B} &= -\frac{m \hat{\mathbf{v}} \times \mathbf{E}}{c_0} + \mu_0 \mu_r \underline{\underline{\alpha}} \cdot \mathbf{H} \end{aligned} \right\}, \quad (6)$$

in the non-co-moving reference frame Σ ; here,

$$\underline{\underline{\alpha}} = \alpha \underline{\underline{I}} + (1 - \alpha) \hat{\mathbf{v}} \hat{\mathbf{v}}, \quad (7)$$

$$\alpha = \frac{1 - \beta^2}{1 - \epsilon_r \mu_r \beta^2}, \quad (8)$$

$$m = \beta \frac{\epsilon_r \mu_r - 1}{1 - \epsilon_r \mu_r \beta^2}. \quad (9)$$

The constitutive relations (6) degenerate to (5) as $v \rightarrow 0$.

In the remainder of this paper, the propagation of plane waves in a medium described by the Minkowski constitutive relations (6) is investigated, with particular emphasis on the unusual behaviour which occurs when $\epsilon_r \mu_r < 1$. For further general background details on planewave propagation within the context of special relativity, the reader is referred to standard works [10]–[12].

2.2 Planewave propagation

Our focus lies on plane waves with field phasors

$$\left. \begin{aligned} \mathbf{E} &= \mathbf{E}_0 \exp(i\mathbf{k} \cdot \mathbf{r}) \\ \mathbf{H} &= \mathbf{H}_0 \exp(i\mathbf{k} \cdot \mathbf{r}) \end{aligned} \right\}. \quad (10)$$

The plane waves are taken to be uniform; i.e., the wavevector $\mathbf{k} = k \hat{\mathbf{k}}$ where the unit vector $\hat{\mathbf{k}} \in \mathbb{R}^3$ and

$$k = k_R + ik_I, \quad (11)$$

where $k_R = \text{Re}\{k\}$ and $k_I = \text{Im}\{k\}$.

As a result of combining the frequency-domain Maxwell curl postulates with the Minkowski constitutive relations and substituting (10) therein, we find that [13]

$$k = k_0 \frac{-\beta \xi \hat{\mathbf{k}} \cdot \hat{\mathbf{v}} \pm \sqrt{\Delta}}{1 - \xi (\beta \hat{\mathbf{k}} \cdot \hat{\mathbf{v}})^2}, \quad (12)$$

wherein

$$\xi = \frac{\epsilon_r \mu_r - 1}{1 - \beta^2}, \quad (13)$$

$$\Delta = 1 + (\epsilon_r \mu_r - 1) \delta, \quad (14)$$

$$\delta = \frac{1 - \left(\beta \hat{\mathbf{k}} \cdot \hat{\mathbf{v}} \right)^2}{1 - \beta^2} \geq 1. \quad (15)$$

Since the two wavenumbers represented by (12) are not independent, the medium with constitutive relations (6) is unirefringent. The choice of sign for the square root term in (12) is dictated by the direction of planewave propagation.

The amplitudes of the electromagnetic field phasors turn out to be [13]

$$\mathbf{E}_0 = C_1 \mathbf{e}_1 + C_2 \mathbf{e}_2, \quad (16)$$

$$\mathbf{H}_0 = \frac{C_1}{\omega \mu_0 \mu_r} \mathbf{e}_2 - \omega \epsilon_0 \epsilon_r C_2 \mathbf{e}_1, \quad (17)$$

where the orthogonal eigenvectors $\mathbf{e}_1$ and $\mathbf{e}_2$ are given by

$$\mathbf{e}_1 = \mathbf{k} \times \hat{\mathbf{v}}, \quad (18)$$

$$\mathbf{e}_2 = \underline{\underline{\alpha}}^{-1} \cdot \left[(\mathbf{k} + m \frac{\omega}{c_0} \hat{\mathbf{v}}) \times \mathbf{e}_1 \right], \quad (19)$$

whereas C_1 and C_2 are arbitrary constants.

Exploiting the relation

$$\mathbf{e}_2 = \mathbf{a} \times \mathbf{e}_1, \quad (20)$$

where

$$\mathbf{a} = \mathbf{k} + \frac{\xi (\omega - \mathbf{k} \cdot \mathbf{v})}{c_0^2} \mathbf{v}, \quad (21)$$

we find the time-averaged Poynting vector

$$\mathbf{P} = \frac{|\mathbf{e}_1|^2 \exp(-2k_I \hat{\mathbf{k}} \cdot \mathbf{r})}{2} \operatorname{Re} \left\{ \frac{|C_1|^2}{\omega \mu_0 \mu_r^*} \mathbf{a}^* + |C_2|^2 \omega \epsilon_0 \epsilon_r^* \mathbf{a} \right\}. \quad (22)$$

2.3 Nondissipative mediums

For nondissipative mediums (i.e., $\epsilon_r \in \mathbb{R}$ and $\mu_r \in \mathbb{R}$), the following three scenarios may be identified:

- (i) If $\epsilon_r \mu_r \geq 1$ then $\Delta > 0$ and the expression (12) represents two real-valued wavenumbers.
- (ii) If $0 < \epsilon_r \mu_r < 1$ then Δ can be either positive- or negative-valued depending upon the magnitude of β and the relative orientations of $\hat{\mathbf{k}}$ and $\hat{\mathbf{v}}$. Hence, either two real-valued wavenumbers or a conjugate pair of complex-valued wavenumbers are represented by (12). In the instance where $v = 0$, we have $\Delta = \epsilon_r \mu_r > 0$ and the wavenumbers are accordingly real-valued.

- (iii) If $\epsilon_r \mu_r < 0$ then $\Delta < 0$ and (12) provides two complex-valued wavenumbers. In the case where $v = 0$, we have $k_R = 0$ which does not correspond to a propagating wave. We exclude this scenario from further consideration.

2.4 Positive, negative and orthogonal phase velocity

Equation (22) for the time-averaged Poynting vector simplifies to

$$\mathbf{P} = \frac{|\mathbf{e}_1|^2 \exp(-2k_I \hat{\mathbf{k}} \cdot \mathbf{r})}{2} \left(\frac{|C_1|^2}{\omega \mu_0 \mu_r} + |C_2|^2 \omega \epsilon_0 \epsilon_r \right) \left[k_R \hat{\mathbf{k}} + \frac{\xi (\omega - k_R \hat{\mathbf{k}} \cdot \mathbf{v})}{c_0^2} \mathbf{v} \right], \quad (23)$$

when $\epsilon_r \in \mathbb{R}$, $\mu_r \in \mathbb{R}$, and $k \in \mathbb{C}$. The phase velocity

$$\mathbf{v}_p = c_0 \frac{k_0}{k_R} \hat{\mathbf{k}}, \quad (24)$$

is described as being positive, negative or orthogonal depending upon its orientation relative to the time-averaged Poynting vector. That is, positive phase velocity (PPV) is characterized by $\mathbf{v}_p \cdot \mathbf{P} > 0$, negative phase velocity (NPV) is characterized by $\mathbf{v}_p \cdot \mathbf{P} < 0$, and orthogonal phase velocity (OPV) is characterized by $\mathbf{v}_p \cdot \mathbf{P} = 0$. In light of (23), the phase velocity for nondissipative mediums is positive, negative or orthogonal depending upon the sign of the scalar

$$W = k_R \left[k_R + \xi \beta \left(k_0 - k_R \beta \hat{\mathbf{k}} \cdot \hat{\mathbf{v}} \right) \hat{\mathbf{k}} \cdot \hat{\mathbf{v}} \right]. \quad (25)$$

We distinguish between the scenarios $\Delta \geq 0$ and $\Delta < 0$ for nondissipative mediums, as follows.

- (a) $\Delta \geq 0$. Here the wavenumber is real-valued and

$$W = k \left[k + \xi \beta (k_0 - k \beta \cos \theta) \cos \theta \right], \quad (26)$$

with θ being the angle between $\hat{\mathbf{k}}$ and $\hat{\mathbf{v}}$.

- (b) $\Delta < 0$. Here the wavenumber is complex-valued, with real and imaginary parts given by

$$\left. \begin{aligned} k_R &= k_0 \frac{-\beta \xi \cos \theta}{1 - \xi (\beta \cos \theta)^2} \\ k_I &= k_0 \frac{\pm \sqrt{\Delta}}{1 - \xi (\beta \cos \theta)^2} \end{aligned} \right\}, \quad (27)$$

and W is null-valued.

3 Numerical illustrations

Let us now illustrate the theory presented in the preceding section by means of some numerical results. In Figure 1, the real and imaginary wavenumbers are plotted as functions of the real-valued product $\epsilon_r \mu_r$ for $\beta \in \{0.3, 0.6, 0.9\}$ with $\theta \in \{\pi/6, \pi/3, 3\pi/4\}$, wherein θ denotes the angle between $\mathbf{k}$ and $\hat{\mathbf{v}}$. The wavenumber generally has a nonzero imaginary part, despite ϵ and μ being real-valued. Furthermore, the positive-valued upper bound on the range of $\epsilon_r \mu_r$ values for which $k_I \neq 0$ increases as the relative speed β increases.

The magnitudes of the phase velocities, corresponding to the wavenumbers presented in Figure 1, are plotted in Figure 2. By definition, the phase velocity is aligned with the direction of $\hat{\mathbf{k}}$.

The positive, negative and orthogonal nature of the phase velocity, as deduced from the sign of the scalar W in (25), are mapped in Figure 2 as functions of β and θ for

$$\epsilon_r \mu_r \in \{0.2, 0.4, 0.6, 0.8, 1.0, 1.2, 1.5, 2, 3, 4, 5, 10\} .$$

The OPV region occupies a substantial portion of the $\beta\theta$ plane for small values of $\epsilon_r \mu_r$. As $\epsilon_r \mu_r$ increases towards unity, the OPV region decreases and vanishes in the limit $\epsilon_r \mu_r \rightarrow 1$. The OPV region is symmetric about the line $\theta = \pi/2$, whereas the NPV region is restricted to those regions of the $\beta\theta$ plane for which $\pi/2 < \theta \leq \pi$ [13] — which shows that NPV arises only when the velocity vector $\mathbf{v}$ casts a negative projection onto the wavevector $\mathbf{k}$. When $\epsilon_r \mu_r = 1$, the phase velocity is positive for all values of β and θ . For $\epsilon_r \mu_r > 1$, OPV does not arise: the phase velocity is either positive or negative, with the NPV region expanding as the product $\epsilon_r \mu_r$ increases.

4 Concluding remarks

Consider a homogeneous medium which is an isotropic dielectric-magnetic medium in a co-moving reference frame Σ' , characterized by the relative permittivity scalar $\epsilon_r > 0$ and the relative permeability scalar $\mu_r > 0$. From this perspective, the medium supports planewave propagation with real-valued wavenumbers, and the phase velocity is directed parallel to the time-averaged Poynting vector.

The nature of planewave propagation is different when viewed in an inertial reference frame Σ , which moves uniformly at velocity $-\mathbf{v}$ relative to Σ' . The following two regimes are then distinguished:

- (a) If $\epsilon_r \mu_r \geq 1$ then all wavenumbers are real-valued, regardless of $\mathbf{v}$. The projection of the phase velocity onto the time-averaged Poynting vector can be either positive or negative, depending upon the magnitude and direction of $\mathbf{v}$.
- (b) If $0 < \epsilon_r \mu_r < 1$ then planewave propagation characterized by both $k \in \mathbb{R}$ and $k \in \mathbb{C}$ (with $k_I \neq 0$) is supported. Whether $k_I \neq 0$ or not depends upon the magnitude of $\mathbf{v}$ and its orientation relative to $\mathbf{k}$. For plane waves with $k_I \neq 0$, the time-averaged Poynting vector is directed orthogonal to the phase velocity.

The regime $0 < \epsilon_r \mu_r < 1$ lies between either vacuum ($\epsilon_r = \mu_r = 1$) or anti-vacuum ($\epsilon_r = \mu_r = -1$) and nihility ($\epsilon_r = \mu_r = 0$) [14, 15, 16]. Anti-vacuum is the vaunted material for the so-called perfect lenses [17]. Many schemes for materials satisfying the condition $0 < \epsilon_r \mu_r < 1$ have been formulated [18, 19, 20], although we must note that dissipation then is hard to avoid. However, our calculations (not reported here) show that the OPV condition can be very nearly satisfied by weakly dissipative materials.

References

- [1] Durney CH and Johnson CC 1969 *Introduction to Modern Electromagnetics* (New York: McGraw-Hill) Chap 6
- [2] Lakhtakia A 1994 *Beltrami Fields in Chiral Media* (Singapore: World Scientific) Chap 7
- [3] Born M and Wolf E 1980 *Principle of Optics, 6th ed* (Oxford: Pergamon) Chap 14
- [4] Lakhtakia A, McCall M W and Weiglhofer W S 2003 Negative phase-velocity mediums *Introduction to Complex Mediums for Optics and Electromagnetics* ed WS Weiglhofer and A Lakhtakia (Bellingham, WA, USA: SPIE Press) pp347–363
- [5] Boardman AD, King N and Velasco L 2005 Negative refraction in perspective *Electromagnetics* **25** 365–389
- [6] Ramakrishna SA 2005 Physics of negative refractive index materials *Rep. Prog. Phys.* **68** 449–521
- [7] Pendry JB (ed) 2003 Focus Issue: Negative Refraction and Metamaterials *Opt. Exp.* **11** http://www.opticsexpress.org/issue.cfm?issue_id=186
- [8] Lakhtakia A and McCall M (eds) 2005 Focus on Negative Refraction *New J. Phys.* **7** <http://www.iop.org/EJ/abstract/1367-2630/7/1/E03>
- [9] Lakhtakia A and Mackay TG 2004 Infinite phase velocity as the boundary between positive and negative phase velocities *Microw. Opt. Technol. Lett.* **41** 165–166
- [10] Chen HC 1983 *Theory of Electromagnetic Waves* (New York: McGraw-Hill) Chap 8
- [11] Pappas CH 1988 *Theory of Electromagnetic Wave Propagation* (New York: Dover Press) Chap 7
- [12] Chawla BR and Unz H 1971 *Electromagnetic Waves in Moving Magneto-plasmas* (Lawrence, KS, USA: University Press of Kansas)
- [13] Mackay TG and Lakhtakia A 2004 Negative phase velocity in a uniformly moving, homogeneous, isotropic, dielectric-magnetic medium *J. Phys. A: Math. Gen.* **37** 5697–5711

- [14] Lakhtakia A 2001 An electromagnetic trinity from “negative permittivity” and “negative permeability” *Int. J. Infrared Millim. Waves* **22** 1731–1734; *ibid* 2002 **23** 813–818.
- [15] Ziolkowski RW 2004 Propagation in and scattering from a matched metamaterial having a zero index of refraction *Phys. Rev. E* **70** 046608.
- [16] Lakhtakia A and Mackay TG 2006 Fresnel coefficients for a permittivity–permeability phase space encompassing vacuum, anti–vacuum, and nihility *Microw. Opt. Technol. Lett.* **48** at press
- [17] Pendry JB 2004 Negative refraction *Contemp. Phys.* **45** 191–2002
- [18] Rachford FJ, Smith DL, Loschialpo PF and Forester DW 2002 Calculations and measurements of wire and/or split–ring negative index media *Phys. Rev. E* **66** 036613
- [19] Simovski CR and He S 2003 Frequency range and explicit expressions for negative permittivity and permeability for an isotropic medium formed by a lattice of perfectly conducting Ω particles *Phys. Lett. A* **311** 254–263
- [20] Paniou NC and Osgood RM 2003 Numerical investigation of negative refractive index metamaterials at infrared and optical frequencies *Opt. Commun.* **223** 331–337




Figure 1: The real (left) and imaginary (right) parts of the wavenumbers k , normalized with respect to k_0 , plotted against $\epsilon_r \mu_r$ for $\beta \in \{0.3, 0.6, 0.9\}$. The values of θ are: 30° (solid curves), 60° (dashed curves) and 135° (broken dashed curves).




Figure 2: The phase velocity, normalized with respect to c_0 , plotted against $\epsilon_r \mu_r$ for $\beta \in \{0.3, 0.6, 0.9\}$. The values of θ are: 30° (solid curves), 60° (dashed curves) and 135° (broken dashed curves). The phase velocity is directed along $\hat{\mathbf{k}}$.




Figure 3: The distribution of positive phase velocity (PPV), negative phase velocity (NPV) and orthogonal phase velocity (OPV), as functions of $\beta \in (0, 1)$ and $\theta \in (0^\circ, 180^\circ)$ for $\epsilon_r \mu_r = 0.2, 0.4, 0.6, 0.8, 1, 1.2, 1.5, 2, 3, 4, 5, 10$. The labels ‘NPV’ and ‘PPV’ shown hold for $\epsilon_r > 0$ and $\mu_r > 0$, but must be reversed for $\epsilon_r < 0$ and $\mu_r < 0$.




Figure 3: continued